



**QIJQ2.E343181**  
**Connectors for Use in Photovoltaic Systems - Component**

Page Bottom

**Connectors for Use in Photovoltaic Systems - Component**

See General Information for Connectors for Use in Photovoltaic Systems - Component

**STAEUBLI ELECTRICAL CONNECTORS ESSEN GMBH**

E343181

Westendstrasse 10  
45143 Essen, GERMANY



Cat. No.	Electrical Rating
<b>Photovoltaic wiring-system connector</b>	
PV-KBT3I, PV-KST3I followed by UR, may be followed by suffix numbers and letters.	600 V dc, 20 A max with 12-14 AWG cable
PV-KBT3II, PV-KST3II followed by UR, may be followed by suffix numbers and letters.	600 V dc, 20 A max with 12 AWG cable
PV-KBT3II, PV-KST3II followed by UR, may be followed by suffix numbers and letters.	600 V dc, 30 A max with 10 AWG cable
PV-KBT3III, PV-KST3III followed by UR, may be followed by suffix numbers and letters.	600 V dc, 30 A max with 10 AWG cable
PV-KBT3/6III, PV-KST3/6III followed by UR, may be followed by suffix numbers and letters.	600 V dc, 30 A max with 8 AWG cable
PV-KST4, PV-KBT4 followed by /2.5 or /5 or /6, followed by "I" or "X" or "II", followed by -UR. or - may be followed by additional suffixes, may be followed by suffix numbers and letters.	600 V dc, 30 A max with 10-14 AWG cable
PV-KST4, PV-KBT4 followed by /2.5 or /5 or /6, followed by "I" or "X" or "II", followed by -UR. or - may be followed by additional suffixes, may be followed by suffix numbers and letters.	1000 V dc, 30 A max with 10-14 AWG cable
PV-KST4, PV-KBT4, followed by /2.5 or /5 or /6, followed by "I" or "X" or "II", followed by -UR. or - may be followed by additional suffixes, may be followed by suffix numbers and letters.	1500 V dc, 30 A max with 10-14 AWG cable
PV-KST4, PV-KBT4 followed by /8, followed by "II", followed by -UR. or - may be followed by additional suffixes, may be followed by suffix numbers and letters.	1500 V dc, 50 A max with 8 AWG cable
PV-SSH4, may be followed by suffix numbers and letters.	n/a
PV-AZS3-UR, PV-AZB3-UR (32.0009-UR, 32.0008-UR), may be followed by suffix numbers and letters.	600 V dc, 30 A max
PV-KST3, PV-KBT3, may be followed by /6, followed by "I", "II" or "III", followed by -UR, may be followed by suffix numbers and letters.	"I" 600 V dc, 20 A max w/ 2.5 mm <sup>2</sup> , 4.0 mm <sup>2</sup> , 14 AWG, 16 AWG, 12 AWG, and 10 AWG cable "II" 600 V dc, 20/30** A max w/ 2.5 mm <sup>2</sup> , 4.0 mm <sup>2</sup> , 14 AWG, 16 AWG, 12 AWG, and 10 AWG cable "III" 600 V dc, 30** A max w/ 2.5 mm <sup>2</sup> , 4.0 mm <sup>2</sup> , 14 AWG, 16 AWG, 12 AWG, and 10 AWG cable "/6 III" 600 V dc, 30 A max w/ 6.0 mm <sup>2</sup> and 8 AWG cable ** 30A rating when assembled to 10 AWG cable only
PV-PLS-S, PV-PLS-B, may be followed by suffix numbers and letters, may be followed by suffix numbers and letters.	1000 Vdc / 600 V dc, 30A max; 10, 12 and 14 AWG PV wires, USE-2 cables (Factory and field assembled connectors on Listed TYLZ Type - USE-2 cables are limited to the max. 600V dc only) 1500 V dc, 30A max.; 10, 12 and 14 AWG PV wires, Factory Wiring Only! (1500V dc only when assembled on Listed cable type Photovoltaic Wire (ZKLA) rated 2000V)
PV-KST4EVO1.0, PV-KBT4EVO1.0 followed by /2.5, followed by I-, followed by a single letter, followed by /L/, followed by a single letter, may be followed by suffix numbers and letters.	600 V dc, 30A max; 14 AWG PV, USE-2 cables
PV-KST4EVO1.0, PV-KBT4EVO1.0 followed by /2.5, followed by I-, followed by a single letter, followed by /M/, followed by a single letter, may be followed by suffix numbers and letters.	1000 V dc, 30A max; 14 AWG PV cables
PV-KST4EVO1.0, PV-KBT4EVO1.0 followed by /2.5 or /6, followed by II-, followed by a single letter, followed by /L/, followed by a single letter, may be followed by suffix numbers and letters.	600 V dc, 30A max; 12 and 14 AWG PV, USE-2 cables

PV-KST4EVO1.0, PV-KBT4EVO1.0 followed by /2.5 or /6, followed by II-, followed by a single letter, followed by /M/, followed by a single letter, may be followed by suffix numbers and letters.	1000 V dc, 30A max; 12 and 14 AWG PV cables
PV-KST4EVO1.0, PV-KBT4EVO1.0 followed by /6, followed by III-, followed by a single letter, followed by /L/, followed by a single letter, may be followed by suffix numbers and letters.	600 V dc, 30A max; 10 and 12 AWG PV, USE-2 cables
PV-KST4EVO1.0, PV-KBT4EVO1.0 followed by /6, followed by III-, followed by a single letter, followed by /M/, followed by a single letter, may be followed by suffix numbers and letters.	1000 V dc, 30A max; 10 and 12 AWG PV cables
PV-ADSP4-S2-UR, PV-ADSP4-S2, PV-ADBP4-S2-UR and PV-ADBP4-S2 followed by /2.5 or /6, may be followed by suffix numbers and letters.	600 V dc, 30A max; 10, 12 and 14 AWG PV, USE-2 cables
<b>PV-ADSP4-S2-UR, PV-ADSP4-S2, PV-ADBP4-S2-UR and PV-ADBP4-S2</b> followed by /2.5 or /6, may be followed by suffix numbers and letters.	1000/1500 V dc, 30A max; 10, 12 and 14 AWG PV cables

Cat. No.	Electrical Rating
<b>Male PV connectors</b>	
PV-KST4-EVO2/2.5, 6 or 10, followed by I, II, III or IV, followed by -UR. Female PV connectors, PV-KBT4-EVO2/2.5, 6 or 10, followed by I, II, III or IV, followed by -UR	1000/1500 V dc, 30 A max with 14 AWG cable 1000/1500 V dc, 35 A max with 12 AWG cable 1000/1500 V dc, 50 A max with 10 AWG cable 1000/1500 V dc, 70 A max with 8 AWG cable
<b>Note:</b> Connectors assembled on Listed TYLZ Type USE-2 cable are limited to the maximum voltage of 600V dc only!	
<b>Note:</b> 1500V dc only when assembled on Listed cable type Photovoltaic Wire (ZKLA) rated 2000V.	
<b>Photovoltaic Connectors (Branch Splitters)</b>	
<b>PV-AZS4 (male), PV-AZB4 (female)</b>	<b>1500 V dc, 50A max.</b>
<b>Note:</b> The ampere and voltage ratings of the Branch Splitters is limited by the intended Input / Output mating connector of series PV-KST4... and PV-KBT4...; connector series PV-KST4-EVO 2/... and PV-KBT4-EVO 2/...; connector series PV-PLS-S, PV-PLS-B. The ampacity rating of these combinations are limited based on the wire size used per the National Electrical Code (NEC) requirements for Free Air applications considering the correction factor.	

Conditions of Acceptability:

1. These devices shall be used only where they will not interrupt the current. The components are marked "Do Not Disconnect Under Load." In addition, the need to include specific instructions in the end-use equipment's manual describing the method of achieving disconnect while not under load shall be considered.
2. These components use a material that has an RTI for Mechanical with Impact less than that required for unrestricted Listing. Consideration shall be given to required mechanical protection in the end use.
3. Connector Nos. PV-KBT3 and PV-KST-3, followed by I, II and III, and Nos. PV-KST4, PV-KBT4, followed by /2.5 or /6, followed by "I" or "II," followed by -UR, have been investigated as acceptable for assembly in the field by qualified electricians with factory-provided tooling.
4. These devices have only been assessed for UL Recognition with specific types of mated connectors within their product family. They have not been assessed to operate with any other similar devices from any other manufacturer
5. Connector Nos. PV-KST4EVO1.0 followed by /2.5, followed by I-, followed by a single letter, followed by /L/ or /M/, followed by a single letter. and Nos. PV-KBT4EVO1.0 followed by /2.5, followed by I-, followed by a single letter, followed by /L/ or /M/, followed by a single letter, have been investigated as assembly in factory only.
6. Connector Nos. PV-KST4EVO1.0 followed by /2.5 or /6, followed by II-, followed by a single letter, followed by /L/, followed by a single letter and Nos. PV-KBT4EVO1.0 followed by /2.5 or /6, followed by II-, followed by a single letter, followed by /L/, followed by a single letter, have been investigated as acceptable for assembly in the field by qualified electricians with factory-provided tooling.
7. Connector Nos. PV-KST4EVO1.0 followed by /2.5 or /6, followed by II-, followed by a single letter, followed by /L/, followed by a single letter and Nos. PV-KBT4EVO1.0 followed by /2.5 or /6, followed by II-, followed by a single letter, followed by /L/, followed by a single letter, have been investigated as acceptable for assembly in the field by qualified electricians with factory-provided tooling.
8. Connector Nos. PV-ADSP4 and PV-ADBP4 followed by /2.5 or /6, have been investigated as assembly in factory only.
- 9 These are locking type connectors that require a tool for separating the male and the female connectors from their mating position.

Marking: Company name or trademark , catalog designation and the Recognized Component Mark  on the device or carton.  
Last Updated on 2017-02-16

[Questions?](#)

[Print this page](#)

[Terms of Use](#)

[Page Top](#)

© 2017 UL LLC

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from UL" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "© 2017 UL LLC".